

RADIANCE INSTRUMENTS LTD	PRODUCT MANUAL		REV.: 2
	PRODUCT	BIG DIGIT COUNTDOWN / UP TIMER	30 MAY 2014
	MODEL	RT101AHMS	Version: 12 PAGE 1 of 1

FEATURES

- Big Digit Display
- 19 hr 59 min or 99min 59 sec Countdown / up
- Loud Buzzer Sound
- Pocket Clip
- Foldaway Stand
- Magnetic attachment

APPLICATIONS

- Cooking
- Laboratory
- Parking
- Refrigeration
- Any time counting purpose



SPECIFICATION

Countdown / up range	19 hours 59 minutes or 99 minutes 59 seconds
Display resolution	1 second in MIN/SEC display and 1 minute in HR/MIN display
Buzzer sound level	75 db at 300mm distance
Time accuracy	±3 seconds every 24 hours
Display size	49(W) x 20.5(H) mm
Digit size	8.3(W) x 18(H) mm
Battery	1.5 volt, type AAA or equivalent x1 piece (included)
Product size	67.5(W) x 60.5(H) x 16.3(D) mm (exclude clip portion)

INSTALLATION

1. Install battery with correct polarity positioning.
2. The unit will display "00 00" and is ready for use.

OPERATION

1. Slide the switch on the back to HR or MIN to select display mode.
2. Press [MIN] / [SEC] or [HR] / [MIN] to set the desired count down time.
3. Press [START/STOP] to start timer. The buzzer will sound when display counts down to "00 00" and will be counting up to indicate the elapsed time.
4. Press [START/STOP] to stop timer and the pre-set value will be displayed (memory function).
5. Press [MIN] / [SEC] and [HR] / [MIN] simultaneously will clear display value to "00 00".
6. Press [START/STOP] to start count up.
7. When the display counts up to the maximum range it will stop.

NOTE

If the timer is not in use for a long period of time, please remove the battery from the battery compartment to prevent battery leakage.